

# TEST CERTIFICATE

**Issued to:** EAE Elektrik Asansör End.  
Insaat San. ve Tic. A.S.  
Akçaburgaz Mahallesi 119, Sokak No: 10  
34510 Esenyurt / Istanbul  
Turkey

**For the product:** Low-voltage busbar trunking system

**Trade name:** EAE

**Type/Model:** KOA 01-II

**Ratings:**  $I_{nc}$  160 A at 50 Hz,  $U_i$  1000 V,  $U_{imp}$  12 kV,  $I_{cw}$  10 kA – 1 s  
For more details see annex

**Manufactured by:** EAE Elektrik Asansör End.  
Insaat San. ve Tic. A.S.  
Akçaburgaz Mahallesi 119, Sokak No: 10  
34510 Esenyurt / Istanbul  
Turkey

**Subject:** Design verification

**Requirements:** IEC 61439-6: 2012  
Clauses: 10.2, 10.3, 10.4, 10.5, 10.9, 10.10, 10.11 and Annex BB, CC, and DD

**Remarks:** Busbar trunking system consists of flange, joint and straight lengths

This Test Certificate is granted on account of an examination by DEKRA, the results of which are laid down in report no. 2172186.01-INC, dated 12 January 2015.

The examination has been carried out on one single specimen of the product, submitted by the manufacturer. The Attestation does not include an assessment of the manufacturer's production. Conformity of his production with the specimen tested by DEKRA is not the responsibility of DEKRA.

Arnhem, 12 January 2015

Number: 2172186.100

DEKRA Certification B.V.

F.S. Strikwerda  
Certification Manager

© Integral publication of this certificate and adjoining reports is allowed

**Overview of product evaluation according to IEC 61439-6:**

IEC 61439-6 Clause	Clause description	Tested ratings	Results
10.2	Strength of material and parts		
10.2.2	Resistance to corrosion	Severity test A: indoor	Pass
10.2.3	Properties of insulating materials		
10.2.3.1	Verification of thermal stability of enclosures	Cover of tap-off facility	Pass
10.2.3.2	Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects	Insulating materials retaining current-carrying parts in position: 960 °C Other insulating materials: 650 °C	Pass
10.2.6	Mechanical impact	IK 09	Pass
10.2.7	Marking		Pass
10.2.101	Ability to withstand mechanical loads		
10.2.101.1	Test procedure for a straight busbar trunking unit	<b>Heavy loads</b>	Pass
10.2.101.2	Test procedure for a joint	Heavy loads	Pass
10.2.101.3	Resistance of the enclosure to crushing	Heavy loads	Pass
10.3	Degree of protection of assembly	<b>IP55</b>	Pass
10.4	Clearances and creepage distances	Clearances > 14 mm, based on U <sub>imp</sub> = 12 kV; Creepage distances > 16 mm, based on U <sub>i</sub> = 1000 V, pollution degree 3, material group IIIa.	Pass
10.5	Protection against electric shock and integrity of protective circuits		
10.5.2	Effective earth continuity between the exposed conductive parts of the assembly and the protective circuit	<b>Earth resistance &lt; 0,1 Ω</b>	Pass
10.5.3	Short-circuit withstand strength of the protective circuit	<b>6 kA - 0,1 s</b>	Pass
10.9	Dielectric properties		
10.9.2	Power-frequency withstand voltage	U <sub>i</sub> 1000 V	Pass
10.9.3	Impulse withstand voltage	U <sub>imp</sub> 12 kV	Pass
10.10	Verification of temperature rise		
10.10.2.3.5	Test of a BT run	160 A	Pass
10.11	Short-circuit withstand strength	I <sub>cw</sub> 10 kA - 1 s (3-phase) I <sub>cw</sub> 6 kA - 1 s (neutral)	Pass

IEC 61439-6 Clause	Clause description	Tested ratings	Results																		
Annex BB	Phase conductor characteristics	$[\mu\Omega/m]$ X : 169 R <sub>20</sub> : 314 R : 379 Z <sub>20</sub> : 356 Z = Z <sub>(1)</sub> = Z <sub>(2)</sub> : 415	Pass																		
Annex CC	Fault-loop zero-sequence impedances	<table border="0"> <tr> <td></td> <td>Phase to Neutral [<math>\mu\Omega/m</math>]</td> <td>Phase to Earth [<math>\mu\Omega/m</math>]</td> </tr> <tr> <td>X<sub>(0)bx</sub> :</td> <td>935</td> <td>1041</td> </tr> <tr> <td>R<sub>(0)b20x</sub> :</td> <td>1383</td> <td>1949</td> </tr> <tr> <td>R<sub>(0)bx</sub> :</td> <td>1683</td> <td>2372</td> </tr> <tr> <td>Z<sub>(0)b20x</sub> :</td> <td>1669</td> <td>2209</td> </tr> <tr> <td>Z<sub>(0)bx</sub> :</td> <td>1925</td> <td>2590</td> </tr> </table>		Phase to Neutral [ $\mu\Omega/m$ ]	Phase to Earth [ $\mu\Omega/m$ ]	X <sub>(0)bx</sub> :	935	1041	R <sub>(0)b20x</sub> :	1383	1949	R <sub>(0)bx</sub> :	1683	2372	Z <sub>(0)b20x</sub> :	1669	2209	Z <sub>(0)bx</sub> :	1925	2590	Pass
	Phase to Neutral [ $\mu\Omega/m$ ]	Phase to Earth [ $\mu\Omega/m$ ]																			
X <sub>(0)bx</sub> :	935	1041																			
R <sub>(0)b20x</sub> :	1383	1949																			
R <sub>(0)bx</sub> :	1683	2372																			
Z <sub>(0)b20x</sub> :	1669	2209																			
Z <sub>(0)bx</sub> :	1925	2590																			
Annex DD	Fault-loop resistances and reactances	<table border="0"> <tr> <td></td> <td>Phase to Phase [<math>\mu\Omega/m</math>]</td> <td>Phase to Neutral [<math>\mu\Omega/m</math>]</td> <td>Phase to PE [<math>\mu\Omega/m</math>]</td> </tr> <tr> <td>X<sub>bx</sub> :</td> <td>331</td> <td>441</td> <td>438</td> </tr> <tr> <td>R<sub>b20xx</sub> :</td> <td>627</td> <td>648</td> <td>837</td> </tr> <tr> <td>R<sub>bx</sub> :</td> <td>763</td> <td>788</td> <td>1018</td> </tr> </table>		Phase to Phase [ $\mu\Omega/m$ ]	Phase to Neutral [ $\mu\Omega/m$ ]	Phase to PE [ $\mu\Omega/m$ ]	X <sub>bx</sub> :	331	441	438	R <sub>b20xx</sub> :	627	648	837	R <sub>bx</sub> :	763	788	1018	Pass		
	Phase to Phase [ $\mu\Omega/m$ ]	Phase to Neutral [ $\mu\Omega/m$ ]	Phase to PE [ $\mu\Omega/m$ ]																		
X <sub>bx</sub> :	331	441	438																		
R <sub>b20xx</sub> :	627	648	837																		
R <sub>bx</sub> :	763	788	1018																		

**Product details:**

Busbars		
3-phase		6 x 20 mm Aluminium conductor
Neutral		6 x 20 mm Aluminium conductor
PE		trunking enclosure

Note: The operational current ratings above are given at 50 Hz, operational currents current at 50 Hz are applicable to 60 Hz for rated currents up to and including 800 A (IEC 61439-1 clause 10.10.2.3.1).